

JJ BENDER

High Volume Laser/Printing Solutions

Canon Image Runner 8070 Specifications

Machine

- **Canon Image Runner 8070**

Type

- Digital, Multifunction Imaging System

Imaging System

- Laser Dry Electrostatic Transfer

Developing System

- Dry Monocomponent Toner Projection

Image Server Memory

- Standard 512MB RAM + 20GB HDD

Interface Connections

- 10/100Base-T (RJ-45), USB 2.0 High Speed

First-Copy Time

- 3.1 Seconds From Platen Glass
- 4.3 Seconds From ADF

Warm-Up Time

- 6 Minutes or Less

Acceptable Originals

- Sheets, Books, 3-Dimensional Items

Max. Original Size

- 11" x 17"

Max. Copy Size

- 11" x 17"

Min. Copy Size

- 4-1/8" x 5-7/8"

Max. Mail Boxes Supported

JJ BENDER LLC

457 Castle Ave. ▪ Fairfield, CT 06825 ▪ Tel: (203) 336-4034 ▪ Fax: (203) 368-4654

www.jjbender.com ▪ mail@jjbender.com

JJ BENDER

High Volume Laser/Printing Solutions

Canon Image Runner 8070 Specifications

- 100

Max. Copy Reservation

- 5 Jobs

Actual Resolution

- 600 dpi x 600 dpi

Interpolated Resolution

- 1200 dpi x 600 dpi (Copy)
- 2400 dpi x 600 dpi (Print)

Halftone

- 256 Gradations of Gray

Copy Speed

- 80 cpm (Letter)
- 40 cpm (11" x 17")

Duplexing

- Standard Automatic Trayless

Magnification Reduction/Enlargement

- 25% to 400% in 1% Increments

Paper Supply

- Standard
 - Dual Front-Loading Trays (1,500 Sheets Each)
 - Dual Front-Loading Cassettes (550 Sheets Each)
 - 50-Sheet Stack Bypass
- Optional
 - 3,500-Sheet Paper Deck-M1/T1 (Total: 7,650 Sheets)

Multiple Copies

- 1 to 9,999

JJ BENDER LLC

457 Castle Ave. ▪ Fairfield, CT 06825 ▪ Tel: (203) 336-4034 ▪ Fax: (203) 368-4654

www.jjbender.com ▪ mail@jjbender.com

JJ BENDER

High Volume Laser/Printing Solutions

Canon Image Runner 8070 Specifications

Paper Weight

- 17 lb. Bond to 110 lb. Index (All Paper Sources)

Toner

- Magnetic Negative Toner – Estimated Yield: 33,000 Images

ACCESSORIES

Automatic Document Feeder

Acceptable Originals

- Statement to Ledger

Scanning Speed

- 55 ppm (Letter)

Capacity

- 100 Sheets (All Sizes/20 lb.)

Paper Weight

- 10 lb. to 32 lb. Bond (One-Sided Scanning)
- 13 lb. to 32 lb. Bond (Two-Sided Scanning)

Finisher-K1N/K2N (Optional)

Number of Trays

- Two

Tray Capacity

- Top Tray
 - 1,000 Sheets (All Sizes)
Offset Stacking
- Lower Tray
 - 2,000 Sheets (Letter)
 - 1,000 Sheets (11" x 17", Legal)
Offset Stacking

Staple Position

JJ BENDER LLC

457 Castle Ave. ▪ Fairfield, CT 06825 ▪ Tel: (203) 336-4034 ▪ Fax: (203) 368-4654

www.jjbender.com ▪ mail@jjbender.com

JJ BENDER

High Volume Laser/Printing Solutions

Canon Image Runner 8070 Specifications

- 1 - Any Corner
- 2 - Side Margin

Max. Stapling Capacity

- 100 Sheets (Letter)
- 50 Sheets (Letter-R/Legal/11" x 17")

Hole-Punch (K2N Only)

- 3 Holes (11" x 17", Letter)
- 2 Holes (Legal, Letter-R)

Saddle Finisher-K3N (Optional)

Number of Trays

- Three

Tray Capacity

- Top Tray
 - 1,000 Sheets (All Sizes)
Offset Stacking
- Lower Tray:
 - 2,000 Sheets (Letter)
 - 1,000 Sheets (11" x 17", Legal)
Offset Stacking
- Saddle-Stitch Tray
 - 30 Sets

Staple Position

- 1 - Any Corner
- 2 - Side Margin

Max. Stapling Capacity

- 100 Sheets (Letter)
- 50 Sheets (Letter-R/Legal/11" x 17")

Hole-Punch

- 3 Holes (11" x 17", Letter)
- 2 Holes (Legal, Letter-R)

JJ BENDER LLC

457 Castle Ave. ▪ Fairfield, CT 06825 ▪ Tel: (203) 336-4034 ▪ Fax: (203) 368-4654

www.jjbender.com ▪ mail@jjbender.com

JJ BENDER

High Volume Laser/Printing Solutions

Canon Image Runner 8070 Specifications

Saddle-Stitch Capabilities

Saddle-Stitch Paper Sizes

- 11" x 17", Letter-R, Legal

Stapling Capacity

- 15 Sheets (60 Pages)

Folding

- V-Folding Standard

Paper Deck-M1/T1 (Optional)

Paper Capacity

- 3,500 Sheets

Paper Size (M1)

- Letter

Paper Size (T1)

- Letter-R, Letter, Legal, 11" x 17"

Paper Weight

- 17 lb. Bond to 110 lb. Index

Document Insertion Unit-B1 (Optional)

Paper Size

- Letter-R to 11" x 17"

Paper Weight

- 17 lb. Bond to 110 lb. Index

Feeder Capacity

- Letter, Letter-R: 100 Sheets
- Legal, 11" x 17": 50 Sheets

Paper Folding Unit-C1 (Optional)

Paper Size

- 11" x 17" Only

JJ BENDER LLC

457 Castle Ave. ▪ Fairfield, CT 06825 ▪ Tel: (203) 336-4034 ▪ Fax: (203) 368-4654

www.jjbender.com ▪ mail@jjbender.com

JJ BENDER

High Volume Laser/Printing Solutions

Canon Image Runner 8070 Specifications

Paper Weight

- 17 lb. to 20 lb. Bond

Fold Type

- Z-Fold

Booklet Trimmer-A1 (Optional)

Sheet Capacity

- 30 Sheets (60 Pages)

Stack Capacity

- 7-1/8" (Approx. 2,000 Pages)

Dust Capacity

- Approx. 2,000 Pages (Letter)

Universal Send Kit-C1 (Optional)

Sending Method

- E-Mail, I-Fax, User Inbox, File Server (IPX, FTP, SMB)

Address Book Capacity

- Maximum 1,800

File Format

- Standard: TIFF, PDF
- Optional: PDF (OCR)

Sending Size

- Statement to Ledger

Scan Density

- 200/300/400/600 dpi

Multi-PDL Printer Kit-F1 (Optional)

Processor

- Canon Custom Processor-Shared

Memory

JJ BENDER LLC

457 Castle Ave. ▪ Fairfield, CT 06825 ▪ Tel: (203) 336-4034 ▪ Fax: (203) 368-4654

www.jjbender.com ▪ mail@jjbender.com

JJ BENDER

High Volume Laser/Printing Solutions

Canon Image Runner 8070 Specifications

- 512MB-Shared

Storage

- 20GB-Shared

PDL Support

- PostScript 3 Emulation
- PCL 5e, PCL 6, UFR II

Protocol Stacks

- Ethernet
 - IPX/SPX™: 802.2, 802.3
 - Ethernet II, 802.2 SNAP
 - TCP/IP
- AppleTalk® Phase II

Network OS

- Novell® NetWare® v3.2, 4.1, 4.11, 4.2, 5, 5.1, 6, 6.5
- Windows® 98/Me/2000/XP
- Windows NT® 4.0, Windows 2003 Server
- Solaris™ 1.1x, 2.5x or Later
- Apple® System 8.0 or Later (PPD)

imagePASS-M3 Print Controller (Optional)

Type

- External Stand-Alone Controller

Processor

- Intel® Celeron® 2.5GHz

Memory

- 256MB

Storage

- 40GB HDD

PDL Support

- Adobe® PostScript 3, PCL 5e, PCL 6

JJ BENDER LLC

457 Castle Ave. ▪ Fairfield, CT 06825 ▪ Tel: (203) 336-4034 ▪ Fax: (203) 368-4654

www.jjbender.com ▪ mail@jjbender.com

JJ BENDER

High Volume Laser/Printing Solutions

Canon Image Runner 8070 Specifications

Interface Connections

- Standard: 10/100/1000Base-T (RJ-45)
- Optional: Parallel Interface Adapter

Network OS

- Novell NetWare v.5.x or Later (IPX/SPX)
- Windows 98/Me/2000/XP
- Windows NT 4.0, Windows 2003 Server
- Solaris 8 or Later
- Apple® Macintosh OS 9.1 or Later,
- OSX 10.2 or Later

Additional Functions

Standard

- Command WorkStation
- Command WorkStation LE (OSX Only)
- Fiery Downloader™

Optional

- Impose
- Hot Folders

Other Accessories

- Card Reader-D1
- Card Sets
- USB Application Interface Board-D1
- Expansion Bus-A1
- imageRUNNER Security Kit-A2
- Universal Send PDF Enhancement Kit-B1
- Barcode Printing Kit
- Web Access Software
- Voice Guidance Kit
- Remote Operator's Software Kit

JJ BENDER LLC

457 Castle Ave. ▪ Fairfield, CT 06825 ▪ Tel: (203) 336-4034 ▪ Fax: (203) 368-4654

www.jjbender.com ▪ mail@jjbender.com